



**GREEN BUTTON: POWER** 

Push in for on, out for off.



**CLOSE LEVER:** FORWARD



YELLOW BUTTON: SPEED SELECTION

Push in for slow, out for fast.



**OPEN LEVER:** REVERSE



**POWER METER** 



**CHARGE PORT** 


#### **READ AND UNDERSTAND BEFORE USE:**

- Ensure the yellow speed button is depressed for lower speed for first use
- Ensure the path to travel is clear of obstacles and people at all times
- Ensure sufficient space behind you when reversing
- Ensure goods are securely loaded
- The machine has a timed delay to reach maximum speed and to stop. Users should familiarise themselves with this prior to use
- The lever is proportional, small displacements give small speed changes
- Use your index finger when using the lever
- Power on, wait for the charge lights to read solid, then slowly move the lever to drive
- Each machine type has a weight limit; ensure this is not exceeded
- Tip the machine to a comfortable position, keep that balance while manoeuvring
- Max laden drop is 3"

# IF IN DOUBT, PLEASE SEEK ADVICE.



SCAN OR CODE FOR CHARGING TIPS. SEE OVERLEAF FOR MORE CHARGING INFO.



### Your charger is capable of charging at 6, 12 & 24 volts

- When plugged in and your batteries are ready to charge the 24v & SLOW / 1A Leds will show
- Once charging at 24volts, touch the MODE button to switch to 2A and leave it there
- A full charge takes 6 hours
- Short 20 minute or even 1 hour charges DO NOT replenish the batteries properly

### The charger will normally charge UNLESS

- Your batteries are too discharged ie below 15 volts
- If below 15 volts, then you will see 12 volts and 100% lights, this means
  NO charge is being made

The key to successful maintenance of your GoodsMan sack truck batteries is:

## **USE IT - CHARGE IT - LEAVE IT ON CHARGE**

#### Redhill Manufacturing Limited

Unit 13-15, Lakeside Industrial Estate, Broad Ground Road, Redditch, Worcestershire, B98 8YP, United Kingdom  $\epsilon$ 

T: +44 (0)1527 529002 | E: sales@redhill.co.uk

